





Dimensions for nuts

Note: When inquiring about 5 digit part numbers beginning with 8, please preface the number with R264-. Example: 88111 should be R264-88111.


Special forms

R264 - article	Dimensions	M 12x1	M 15x1	M 17x1	M 20x1	M 25x1.5	M 30x1.5
88081 	d ₂	21	24	28	32	38	44
	d ₃	18	21	24	27	33	38
	h	7.6	8.6	8.7	9.6	10.5	10.7
	m	4.5	5.5	5.5	6	6.5	6.6
	b	3	4	4	4	5	5
	t	1.5	1.5	2	2.5	2.5	3
	qty. slots	4	4	4	4	4	4
	Dimensions	M 35x1.5	M 40x1.5	M 45x1.5	M 50x1.5	M 55x2	M 60x2
	d ₂	50	56	62	68	75	80
	d ₃	44	50	55	61	68	73
h	11.3	12.3	12.3	12.9	13.4	13.4	
m	7	7.7	7.8	8.1	8.2	8.2	
b	5	6	6	6	7	7	
t	3	3	3.5	3.5	3.5	3.5	
qty. slots	4	4	4	4	6	6	

locknuts GUK

R264 - article	Dimensions	M 6	M 8	M 10	M 12	M 16	M 20
88088 	d	10	11	13	15	20	25
	l	20/25/ 30/40	20/25/30/ 40/45	25/30/ 40/50	30/40/ 50	40	50


round couplings

R264 - article	Dimensions	TR 12x3	TR 14x4	TR 16x4	TR 18x4	TR 20x4	TR 22x5	TR 24x5
88089 	d	22	36	36	36	36	50	50
	l	18	21	24	27	30	33	36
	Dimensions	TR 26x5	TR 28x5	TR 30x6	TR 32x6	TR 36x6	TR 40x7	TR 44x7
	d	50	60	60	60	75	75	75
l	39	42	45	48	54	60	66	

round nuts with trapezoidal thread

R264 - article	Dimensions	M 3	M 4	M 5	M 6	M 8	M 10	M 12	M 16
88106 	d ₂ *	4.5	5.5	6.5	8	10	12.5	14.5	18.5
	d ₃	4.7	5.7	6.75	8.3	10.3	12.85	14.85	18.85
	d ₄	4.5	5.5	6.5	8	10	12.5	14.5	18.5
	m	3	3.2	4	5	6.5	8	10	13
	f	0.4	0.4	0.4	0.4	0.9	0.9	1.3	1.5
	h	0.9	0.9	0.9	0.9	1.9	1.9	2.9	2.4
	s	5.5	7	8	10	13	15	17	22

rivet nuts
* corresponds to drill hole diameter with tol. H11

R264 - article	Dimensions	M 4	M 5	M 6	M 8	M 10
88108 	d ₂	15	17	19	22	25
	d ₃	5	6.5	7.5	10	11.5
	h	6	8	9/12	11/15	13
	a	5	7	7	9	11

tee nuts with prong